

## Quantec Monitoring Point, Button Reset

Part No. QT604



### Overview

- A keyswitch-isolatable monitoring point c/w a RESET button for cancelling calls.
- Can be configured to generate a Standard or Emergency call when a fire exit or drug cupboard is opened (via magnetic contacts) or a telephone or door bell rings.
- Can be used to monitor any device with a normally open or normally closed switch - ideal for interfacing PIRs, strip switches, flow switches and other devices to Quantec.
- Red/green reassurance LED.
- When isolated, the QT604's reassurance LED will illuminate Green and the monitored door or device may be opened and closed without signalling a call on the system.
- Mounts on a standard UK 25mm single gang flush or surface back box.
- QT604M secure magnetic reset version also available.



### More Information

### Technical Specifications

Quiescent current	TBC.
Alarm current	TBC.
Indicators	Red/Green Reassurance LED (lit green when device is isolated).



Controls	Isolation keyswitch (switches monitoring off when ISOLATED); Reset button (cancels calls made from the monitoring point and from devices wired on the same Zone). Note that a QT604M magnetic reset v
Connections	Net +; Net -; R; G; L+; SW
Expansion connections	R (Red) and G (Green) connections allow the connection of an optional slave overdoor light. Alternatively G (Green) and SW (Switch) can be used for an optional Call Alert Unit allowing telephone mo
Onboard 6.35mm Remote Jack Socket	No.
Onboard Infrared Receiver	No.
Product dimensions (mm)	87 W x 87 H x 29 D mm. Mounts on a UK 25mm single gang back box.
Construction & finish	Plastic.
IP Rating	IP41.
Weight	90g.
Operating conditions/temperature	-5°C to +40°C. Max. relative humidity 95% non-condensing.



T 01942 322744 E sales@c-tec.co.uk  
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom